

WINSTAR Display

OLED SPECIFICATION

Model No:

WEO012864AM

General Specification

Item	Dimension	Unit
Dot Matrix	128 x 64	—
Module dimension	73.0 × 41.86 × 2.01	mm
Active Area	61.41 × 30.69	mm
Pixel Size	0.45 × 0.45	mm
Pixel Pitch	0.48 × 0.48	mm
Display Mode	Passive Matrix	
Display Color	Monochrome	
Drive Duty	1/64 Duty	
IC	SH1106	
Interface	I2C, 4-Wire SPI ,6800, 8080	
Size	2.7 inch	


Technical drawing of a 2.7-inch TFT-LCD module, showing dimensions and labels for the top and side views.

Top View Dimensions:

- Overall Width: 73 ± 0.2
- Overall Height: 41.80 ± 0.2
- Active Area: 2.7" 128x64 Pixels
- Dimensions from Left Edge to Active Area Start:
 - 0.5
 - 36.5 (Pol.)
 - 32.69 (VA)
 - 30.69 (AA)
- Dimensions from Active Area End to Right Edge:
 - 0.5
 - 72 (Pol.)
 - 63.41 (VA)
 - 61.41 (AA)
- Dimensions from Top Edge to Active Area Start:
 - 0.5
 - 4.795
 - 5.795
- Dimensions from Active Area End to Top Edge:
 - 0.5
 - 2.19
 - 3.19

Side View Dimensions:

- Overall Thickness: 2.01 ± 0.2
- Dimensions from Front Face to Back Face:
 - 0.7
 - 1.1
- Shading Tape: (10) (14) (1)
- Glue: 2.0 Max. (Non-Bending area)
- Contact Side: 4
- Stiffener: 0.3 ± 0.03
- Dimensions from Bottom Edge to Active Area Start:
 - 28.5 \pm 0.5
 - 16 \pm 0.1
- Dimensions from Active Area End to Bottom Edge:
 - 0.5
 - 1
- Dimensions from Top Edge to Active Area Start:
 - 7
 - 2.5
- Dimensions from Active Area End to Top Edge:
 - 1
 - 2- ϕ 1
- Dimensions from Bottom Edge to Active Area End:
 - W=0.28
 - P0.5*30=15



The non-specified tolerance of dimension is ± 0.3 mm.

Interface Pin Function

No.	Symbol	Function															
1	ESD_GND	ESD Ground pin															
2	VSS	Ground.															
3-10	NC	No connection															
11	VDD1	Power supply input															
12	IM1	These are the MPU interface mode select pads.															
		<table><tr><td></td><td>8080</td><td>I2C</td><td>6800</td><td>4-wire SPI</td></tr><tr><td>IM1</td><td>1</td><td>1</td><td>0</td><td>0</td></tr><tr><td>IM2</td><td>1</td><td>0</td><td>1</td><td>0</td></tr></table>		8080	I2C	6800	4-wire SPI	IM1	1	1	0	0	IM2	1	0	1	0
			8080	I2C	6800	4-wire SPI											
IM1	1	1	0	0													
IM2	1	0	1	0													
13	IM2	Note (1) 0 is connected to VSS (2) 1 is connected to VDD1															
14	NC	No connection															
15	$\overline{\text{CS}}$	This pad is the chip select input. When $\overline{\text{CS}}$ = “L”, then the chip select becomes active, and data/command I/O is enabled.															
16	$\overline{\text{RES}}$	This is a reset signal input pad. When $\overline{\text{RES}}$ is set to “L”, the settings are initialized. The reset operation is performed by the $\overline{\text{RES}}$ signal level.															
17	A0	This is the Data/Command control pad that determines whether the data bits are data or a command. A0 = “H”: the inputs at D0 to D7 are treated as display data. A0 = “L”: the inputs at D0 to D7 are transferred to the command registers. In I2C interface, this pad serves as SA0 to distinguish the different address of OLED driver.															
18	$\overline{\text{WR}}$ (R/ $\overline{\text{W}}$)	This is a MPU interface input pad. When connected to an 8080 MPU, this is active LOW. This pad connects to the 8080 MPU $\overline{\text{WR}}$ signal. The signals on the data bus are latched at the rising edge of the $\overline{\text{WR}}$ signal. When connected to a 6800 Series MPU: This is the read/write control signal input terminal. When R/ $\overline{\text{W}}$ = “H”: Read. When R/ $\overline{\text{W}}$ = “L”: Write.															

19	E/ $\overline{\text{RD}}$	<p>This is a MPU interface input pad.</p> <p>When connected to an 8080 series MPU, it is active LOW. This pad is connected to the $\overline{\text{RD}}$ signal of the 8080 series MPU, and the data bus is in an output status when this signal is "L".</p> <p>When connected to a 6800 series MPU, this is active HIGH. This is used as an enable clock input of the 6800 series MPU.</p> <p>When $\overline{\text{RD}}$ = "H": Enable.</p> <p>When $\overline{\text{RD}}$ = "L": Disable.</p>
20~27	D0~D7	<p>This is an 8-bit bi-directional data bus that connects to an 8-bit or 16-bit standard MPU data bus.</p> <p>When the serial interface is selected, then D0 serves as the serial clock input pad (SCL) and D1 serves as the serial data input pad (SI). At this time, D2 to D7 are set to high impedance.</p> <p>When the I2C interface is selected, then D0 serves as the serial clock input pad (SCL) and D1 serves as the serial data input pad (SDAI). At this time, D2 to D7 are set to high impedance.</p>
28	IREF	This is a segment current reference pad. A resistor should be connected between this pad and VSS. Set the current at 18.75uA.
29	VCOMH	This is a pad for the voltage output high level for common signals. A capacitor should be connected between this pad and VSS.
30	VPP	OLED panel power supply. It could be supplied externally. A capacitor should be connected between this pad and VSS.
31	ESD_GND	ESD Ground pin

Absolute Maximum Ratings

Parameter	Symbol	Min	Max	Unit
Supply Voltage for Logic	VDD1	-0.3	3.6	V
Supply Voltage for Display	VPP	-0.3	14.5	V
Operating Temperature	TOP	-40	+80	°C
Storage Temperature	TSTG	-40	+85	°C

Electrical Characteristics

DC Electrical Characteristics

Item	Symbol	Condition	Min	Typ	Max	Unit
Supply Voltage for Logic	VDD1	—	1.65	3.0	3.3	V
Supply Voltage for Display	VPP	—	6.4	13.0	13.5	V
High Level Input	VIH	—	$0.8 \times VDD1$	—	VDD1	V
Low Level Input	VIL	—	VSS	—	$0.2 \times VDD1$	V
High Level Output	VOH	—	$0.8 \times VDD1$	—	VDD1	V
Low Level Output	VOL	—	VSS	—	$0.2 \times VDD1$	V
Display 50% Pixel on	IPP	VPP = 13V	—	24	36	mA